

FRS Radios Frequency Chart

<u>CH. No.</u>	<u>Frequency</u>	<u>Cross Ref.</u>	<u>CH. No.</u>	<u>Frequency</u>	<u>Cross Ref.</u>
1	462.5625	FRS & GMRS 1	12	467.6625	FRS 12
2	462.5875	FRS & GMRS 2	13	467.6875	FRS 13
2	462.6125	FRS & GMRS 3	14	467.7125	FRS 14
4	462.6375	FRS & GMRS 4	15	462.550	GMRS 11
5	462.6625	FRS & GMRS 5	16	462.575	GMRS 8
6	462.6875	FRS & GMRS 6	17	462.600	GMRS 12
7	462.7125	FRS & GMRS 7	18	462.625	GMRS 9
8	467.5625	FRS 8	19	462.650	GMRS 13
9	467.5875	FRS 9	20	462.675	GMRS 10
10	467.6125	FRS 10	21	462.700	GMRS 14
11	467.6375	FRS 11	22	462.725	GMRS 15

CTCSS Chart

<u>Code</u>	<u>Tone</u>
1	67
2	71.9
2	74.4
4	77
5	79.7
6	82.5
7	85.4
8	88.5
9	91.5
10	94.8
11	97.4

<u>Code</u>	<u>Tone</u>
12	100
13	130.5
14	107.2
15	110.9
16	114.8
17	118.8
18	123
19	127.3
20	131.8
21	136.5
22	141.3

<u>Code</u>	<u>Tone</u>
23	146.2
24	151.4
25	156.7
26	162.2
27	167.9
28	173.8
29	179.9
30	186.2
31	192.8
32	203.5
33	210.7

<u>Code</u>	<u>Tone</u>
34	218.1
35	225.7
36	233.6
37	241.8
38	250.3